



100GBASE-ER4 1310nm SMF 40km QSFP28 Optical Transceiver with Duplex LC Connector

Model No. 100GERSFPCL

DESCRIPTION

The QSFP28 transceiver modules are designed for use in 100 Gigabit Ethernet links on up to 40 km of single mode fiber. Digital diagnostics functions are available via the I2C interface, as specified by the QSFP28 MSA.

FEATURES

- Hot-pluggable QSFP28 form factor
- Power dissipation < 4.5W
- Single 3.3V power supply
- RoHS-6 Compliant (lead-free)
- Case Temperature Operating Range: 0°C to 70°C
- 4x25 Gb/s transmitter
- 4x25G retimed electrical interface
- Duplex LC receptacle
- I2C management interface
- Up to 30km reach for G.652 SMF without FEC
- Up to 40km reach for G.652 SMF with FEC

APPLICATION

- 100G Ethernet
- Data Center Interconnect



ABSOLUTE MAXIMUM RATINGS

PARAMETER	SYMBOL	MIN	MAX	UNIT
Storage Temperature	T _s	-20	85	°C
3.3V Power Supply Voltage	V _{CC}	-0.5	3.6	V
Relative Humidity	RH	5	85	%

Note: Exceeding these values may cause permanent damage. Function operation under these conditions is not implied.

RECOMMENDED OPERATING CONDITIONS

PARAMETER	SYMBOL	MIN	TYP.	MAX	UNIT	NOTES
Case Temperature	T _C	0		70	°C	
Power Supply Voltage	V _{CC}	3.14	3.3	3.46	V	
Power Dissipation				4.5	W	@3.3V

ELECTRICAL CHARACTERISTICS

PARAMETER	SYMBOL	MIN	TYP.	MAX	UNIT
Data Rate, per lane			25.78125		Gbps
LP Mode/Reset/ModselL	V _{IL}	-0.3		0.8	V
LP Mode/Reset/ModselL	V _{IH}	2		V _{CC} +0.3	V
ModPrsL/IntL	V _{OL}	0		0.4	V
ModPrsL/IntL	V _{OH}	V _{CC} -0.5		V _{CC} +0.3	V

Lasermate Group, Inc.

19608 Camino De Rosa, Walnut, CA 91789, USA

Tel: (909)718-0999 | Fax: (909)718-0998 | E-mail: info@lasermate.com | URL: <http://www.lasermate.com>




TRANSMITTER OPTICAL CHARACTERISTICS

PARAMETER	SYMBOL	MIN	TYP.	MAX	UNIT
Operating Data Rate	DR		25.78125		Gbps
Total Average Launch Power	Pt			10.5	dBm
Average Launch Power, per Lane		-2.9		4.5	dBm
Extinction Ratio	ER	6.5			dB
Optical Modulation Amplitude, per lane	P _{oma}	-0.5			dBm
Transmitter Dispersion Penalty, each lane	TDP			2.5	dB
Lane Center Wavelength	L0	1294.53	1295.56	1296.59	nm
	L1	1299.02	1300.05	1301.09	
	L2	1303.54	1304.58	1305.63	
	L3	1308.09	1309.14	1310.19	
Side Mode Suppression	SMSR	30			dB
Transmitter Reflectance	R _T			-12	dB
Disable Output Power	P _{o_off}			-30	dBm
Output Eye Mask Definition {X1, X2, X3, Y1, Y2, Y3}		{0.25, 0.4, 0.45, 0.25, 0.28, 0.4}			


RECEIVER OPTICAL CHARACTERISTICS

PARAMETER	SYMBOL	MIN	TYP.	MAX	UNIT	NOTES
Damage Threshold, per lane	Pth	-4			dBm	
Receiver Sensitivity (OMA), per lane	Sen1			-14.7	dBm	BER = 1x10 ⁻¹²
Stressed Receiver Sensitivity in OMA, per lane				-12.7	dBm	BER = 1x10 ⁻¹²
Receiver Sensitivity (OMA), per lane	Sen2			-18.7	dBm	BER = 5x10 ⁻¹²
Stressed Receiver Sensitivity (OMA), per lane				-16.7	dBm	BER = 5x10 ⁻¹²
Receiver Reflectance	R _R			-26.0	dB	
LOS De-Assert	LOSD		-24		dBm	
LOS Assert	LOSA		-26		dBm	
LOS Hysteresis		0.5			dB	

PAD ASSIGNMENT AND DESCRIPTION



Top Side
Viewed From Top



Bottom Side
Viewed From Bottom




PIN	LOGIC	SYMBOL	DESCRIPTION	PLUG SEQUENCE	NOTE
1		GND	Ground	1	Note 1
2	CML-I	Tx2n	Transmitter Inverted Data Input	3	
3	CML-I	Tx2p	Transmitter Non-Inverted Data Input	3	
4		GND	Ground	1	Note 1
5	CML-I	Tx4n	Transmitter Inverted Data Input	3	
6	CML-I	Tx4p	Transmitter Non-Inverted Data Input	3	
7		GND	Ground	1	Note 1
8	LVTTL-I	ModSelL	Module Select	3	
9	LVTTL-I	ResetL	Module Reset	3	
10		Vcc Rx	+3.3V Power Supply Receiver	2	Note 2
11	LVCMOS-I/O	SCL	2-wire serial interface clock	3	
12	LVCMOS-I/O	SDA	2-wire serial interface data	3	
13		GND	Ground	1	Note 2
14	CML-O	Rx3p	Receiver Non- Inverted Data Output	3	
15	CML-O	Rx3n	Receiver Inverted Data Output	3	
16		GND	Ground	1	Note 1
17	CML-O	Rx1p	Receiver Non- Inverted Data Output	3	
18	CML-O	Rx1n	Receiver Inverted Data Output	3	
19		GND	Ground	1	Note 1
20		GND	Ground	1	Note 1
21	CML-O	Rx2n	Receiver Inverted Data Output	3	
22	CML-O	Rx2P	Receiver Non- Inverted Data Output	3	
23		GND	Ground	1	Note 1
24	CML-O	Rx4n	Receiver Inverted Data Output	3	
25	CML-O	Rx4p	Receiver Non- Inverted Data Output	3	
26		GND	Ground	1	Note 1
27	LVTTL-O	ModPrsL	Module Present	3	
28	LVTTL-O	IntL	Interrupt	3	
29	LVCMOS-I/O	Vcc Tx	+3.3V Power Supply transmitter	2	Note 2
30		Vcc1	+3.3V Power Supply	2	Note 2
31	LVTTL-I	LPMODE	Low Power Mode	3	
32		GND	Ground	1	Note 1
33	CML-I	Tx3p	Transmitter Non- Inverted Data Input	3	
34	CML-I	Tx3n	Transmitter Inverted Data Input	3	
35		GND	Ground	1	Note 1
36	CML-I	Tx1p	Transmitter Non- Inverted Data Input	3	
37	CML-I	Tx1n	Transmitter Inverted Data Input	3	
38		GND	Ground	1	Note 1



Note 1: GND is the symbol for signal and supply (power) common for the QSFP module. All are common within the QSFP+ module and all module voltages are referenced to this potential unless otherwise noted. Connect these directly to the host board signal-common ground plane.

Note 2: Vcc Rx, Vcc1 and Vcc Tx are the receiver and transmitter power supplies and shall be applied concurrently. Requirements defined for the host side of the Host Edge Card Connector are listed in Table. Recommended host board power supply filtering is shown in Host board power supply circuit. Vcc Rx Vcc1 and Vcc Tx may be internally connected within the QSFP+ module in any combination. The connector pins are each rated for a maximum current of 500 mA.


DIMENSIONS



Unit: mm


All Dimensions are $\pm 0.20\text{mm}$ Unless Otherwise Specified

HOST BOARD POWER SUPPLY CIRCUIT






RECOMMENDED INTERFACE CIRCUIT





MEMORY MAP



Note: The specifications subject to change without notice.

Lasermate Group, Inc.

19608 Camino De Rosa, Walnut, CA 91789, USA

Tel: (909)718-0999 | Fax: (909)718-0998 | E-mail: info@lasermate.com | URL: <http://www.lasermate.com>